



Hanwha Vision

June 2023



Technical Newsletter

June Contents

Technical Information

- SSM v2.13.01 update
- Wisenet viewer Ver. 1.04.00 update
- SSM settings for automatic backup and recovery
- 2.5g & 5g Desiccant parts

Latest F/W Information

Technical Information

SSM Ver. 2.13.01 Update

Technical Newsletter June 2023

Info. Type Quality Settings Repair S/W Etc

1. Model: SSM Server, SSM PC Console Client, SSM Virtual Matrix

2. Version : SSM v2.12.00 → **v2.13.01**

3. Update : Refer to Release note for detail

category		contents
NEW FEATURES & IMPROVEMENTS	NEW FEATURES	<ul style="list-style-type: none"> - Support display digital zoom ratio value. - Added LPR search type for AI NVR in Object Search tab - Add version mismatch notification UI between client and server
	IMPROVEMENTS	<ul style="list-style-type: none"> - Support showing speaker IP display at event action - Support forwarding child server failover information to federation parent server - Support normal close event conditions for alarm input of ADAM-6050 - Change RootCA certificate company name - (Hanwha Techwin > Hanwha Vision)
BUG FIXES		<ul style="list-style-type: none"> - Fixed the abnormal memory usage issue of SUNAPI server. - Fixed an issue when request the smart search with PRN-6400DB4, the request fails from the 4th request - Improved the issue of not receiving BestShots after deleting and reinstalling WiseAI open platform applications - Fixed an issue where the layout sequence behaved abnormally, when a map layout was included in the sequence setup on VMD. - Fixed media server crash, when using ONVIF/RTSP cameras. - Fixed camera setup page authentication error in NVR setup page opened in Configuration Manager. - Fixed an issue where the UI language in Japanese was displayed incorrectly. - Fixed an issue where the license information was displayed incorrectly. - Fixed the synchronization problem of clustering data.
NEW DEVICE SUPPORT		<ul style="list-style-type: none"> - SSM Core Server/Console Client/VM <ul style="list-style-type: none"> ` IP camera: TNV-C7013RC ` controller: SPC-2001

※ Downloadable at <https://www.hanwha-security.com>

Technical Information

Wisenet Viewer Ver. 1.04.00

Technical Newsletter June 2023

Info. Type Quality Settings Repair S/W Etc

1. Model : NVR/DVR Management software Wisenet Viewer

2. Version : Ver. 1.03.00 → **Ver.1.04.00**

3. Release : May 2023

4. v1.04.00

category	contents
NEW FEATURES & IMPROVEMENTS	<ul style="list-style-type: none"> - Support backup masking function(Refer to the manual for detail) - Masking applied image  <ul style="list-style-type: none"> - Send usage statistics
	<ul style="list-style-type: none"> - Activates only the registered device when registering - Sort by name for sequence items layout - Sort by notification page name
BUG FIXES	<ul style="list-style-type: none"> - Intermittent crash issue when registering P2P equipment - Occurrence of some backup failures

5. Backup masking function

- A license is required to use the backup masking feature.
- It is released as a dedicated server [SSM-ST46] with a backup masking license installed, it does not sellable as separately

※ Downloadable at <https://www.hanwhavision.com>

Technical Information

SSM settings for automatic backup and recovery

Technical Newsletter June 2023

Info. Type Quality Settings Repair S/W Etc

1. Models

- PRP-5000H16, PRP-4000H8, XRP-4310DB4, XRP-4210B4, XRP-4110B2, XRP-4010B2
XRP-4010B2, Wisenet SSM 2.xx SW

2. Purpose

- By using automatic backup of SSM, recover the latest DB when reinstalling/repairing

3. Automatic Backup

- Create in the SSMBackup folder for the first drive to be found except C drive
- Generated in the form of YYYYMMDDHHMMSS (date, time, and minutes) of the backup

This PC > Local Disk (D:) > SSMBackup >			
	Name	Date modified	Type
Downloads	20220419083232	4/19/2022 8:32 AM	File folder
Documents	20220429085748	4/29/2022 8:57 AM	File folder
Pictures	20220528135344	5/28/2022 1:53 PM	File folder
2023년	20220716151225	7/16/2022 3:12 PM	File folder
2023년			

- A function to automatically back up licenses, System Manager, media servers, device certificates, and XNS settings

Name	Date modified	Type	Size
41283557622028253_base.v2c License	3/10/2022 10:17 AM	V2C File	3 KB
1112539362476978376_provisional.v2c	11/30/2021 3:14 PM	V2C File	3 KB
mediaserver.ssmdb	3/30/2022 3:52 PM	SSMDB File	40 KB
mediaserver.ssmdb-shm Media server	4/18/2022 8:06 AM	SSMDB-SHM File	32 KB
mediaserver.ssmdb-wal	4/18/2022 8:06 AM	SSMDB-WAL File	0 KB
PG_backup.cab system manager	4/19/2022 8:32 AM	Cabinet File	247 KB
xns2_dll_settings.ini XNS	12/21/2021 8:18 PM	Configuration settings	2 KB

- Up to five backups are created, and the oldest folder is deleted and created when a new backup is made
- The first backup is performed 24 hours after the Service Manager starts running, and followed by weekly backups
- If drive space is less than or equal to 2GB, delete and create the oldest folder regardless of the number of backup folders

4. Recovery

- Restore of automatically backed up DBs is not provided by default (Patch required)
- Restoring automatically backed up DB will be added in SSM 2.14.00 in the future
- Contact your headquarters technical support representative for restoration

Technical Information

2.5g & 5g Desiccant parts

Technical Newsletter June 2023

Info. Type

Quality Settings Repair S/W Etc

1. Model : All devices applied with desiccant

Weight	DesiKhan 2.5g (New)	DesiKhan 5g
Part	PM02-006317A [2ea] PM02-006172A [50ea]	PM02-006316A [2ea] PM02-006173A [50ea]
Model	PNM-7002VD/9000VD/9002VQ XNF-8010RV, XNP-6040/6040H/6120H, XNV-6010/6020R//8020R/8030R/8040R, XNV-6080/6080R/6085/6085R8080R, XNV-L6080/L6080R QNE-8011R/8021R, QNO-6072R/6073R/7080R, QNV-6012R/6014R/6020R/6022R/6032R, QNV-7010R/7012R/7020R/7022R/7030R, QNV-7032R/7080R/8010R/8020R LNO-6010R/6020R/6020RA/6030R, LNV-6010R/6012R/6020R/6022R/6032R, SCO-6020/6025R/6085R HCO-6020R, HCV-6070R/6080R/6080RW, HCV-7010RA/7020RA/7030RA, HCV-7070R/7070RA/7080R KNO-V2010R/V2020R, KNP-2120H ANE-L6012R/L7012L/L7012R, ANV-L6012R/L7012R	XNF-9010R/9013R, XNV-6013M XNO-6010R/6020R/L6020R/L6021R/L6030R, XNO-8020R/8030R/8040R QNB-2020RH/2080RH/5010RH, QNB-5020RH/7010RH/7080RH QNO-6010R/-12R/-14R/-20R/-22R/-30R/-32R, QNO-6071R/-80R/-81R/-82R/-83R/-84R, QNO-7010R/-12R/-20R/-22R/-30R/-32R/-82R, QNO-8010R/8020R/8030R, QNV-6072R/6073R/6082R/6083R/6084R, QNV-7082R, QNV-8080R/8081R LNO-6012R/6022R/6032R/6070R/6072R, LNV-6070R/6071R/6072R SCO-6083R/6085R, SNO-6012R/6022R/K2083R/L5083R/L6083R, SUO-6083R/6085R, TNB-6030/6031 HCO-7010R/7020R/7030R, HCO-6070R/6080R/6080R/7070R/7080R KNO-2010R/4010R/4080R/5020R, KNO-L2020R/-22R/-80R, VPM-4040OR, KNO-L5010R/-20R, V2012R/-22R/-70R/-72R ANB-2010RH/5010RH, ANV-L6082R/L7082R ANO-2020R/5010R/X2020R ANO-L6012R/-22R/-82R/L7012R/-22R/-82R

2. Caution for handling

- Check the color of 'HUMIDITY INDICATING': Green(Good to use), Purple(Needs to be disposed)
- Store DesiKhan in airtight container after opening the packaging (Dispose after 24hrs)



[Indicator] : Purple(Needs to be disposed)

Airtight container (Dispose after 24hrs)

Latest F/W Information

DVR

Technical Newsletter June 2023

Model	Filename	Date	Version	Release Note
HRX-420/421	HRX-421_3.05.42 _220222110611			- Fixed an issue where the wait icon was displayed intermittently for a long time when entering the playback screen
HRX-820/821 HRX-1620/1621	HRX-1621_3.05.42 _220222110713	2022/03/07	3.05.42	
HRX-434/435	HRX-435_4.52.22 _230206120433			
HRX-1632 HRX-835	HRX-1632_4.52.22_2302101 01358	2023/02/28	4.52.22	- HDD performance improved
HRX-1634/1635 HRX-835A	HRX-1635_5.31.11 _230328135226	2023/04/13	5.31.11	- Added new features and bug fixed, find release note for detail

NVR

Model	Filename	Date	Version	Release Note
XRN-820S XRN-1620SB1/B2 XRN-3210B2/RB2/B4 XRN-6410B2/RB2 XRN-6410B4/DB4 PRN-1600B2 PRN-3200B2/B4 PRN-6400B4/DB4	PRN-6400DB4_5.30.42 _230424163326	2023/05/10	5.30.42	<ul style="list-style-type: none"> - Fixed mouse not clicking intermittently in live mode - Fixed event time output error when searching POS of SSM - Fixed the problem that video reception error occurs when receiving camera video in HTTPS mode - Fixed an error in video reception when registering URL of RTSP UDP multicast - Records HDD number when "HDD error" or "HDD verification required" log occurs - Fixed an issue where "video loss" was displayed when a sequence was running
QRN-430S XRN-420S	XRN-420S_5.01.32 _230206102106	2023/02/28	5.01.32	- HDD performance improved
QRN-830S QRN-1630S XRN-815S	QRN-1630S_5.06.32 _230206123427	2023/03/28	5.06.32	- HDD performance improved
LRN-1610S	LRN-1610S_3.06.22 _220318102605			
LRN-410S/810S	LRN-810S_3.06.22 _220318111208			
QRN-1620S	QRN-1620S_3.06.22 _220318102444			
QRN-420S/820S	QRN-820S_3.07.22 _220318111808			
XRN-1610/A XRN-1610S/SA	xrn-1610s-pkg_v2.48 _210621173533	2021/06/30	2.48	- Added USB device format on backup menu
XRN-2010/A XRN-2011A	xrn-2010-pkg_v2.46 _210315134145	2021/06/14	2.46	<ul style="list-style-type: none"> - Decoding improvements on WN7 camera H.265 - Improved ONVIF third-party camera reboot - Fixed Web server responding issues - Fixed HDD No. to be logged in the event of HDD problems
XRN-3010A	xrn-3010-pkg_v2.46 _210315134112	2021/06/14	2.46	
XRN-410S/810S	XRN-X10X-PKG_v2.46 _210204185920	2021/02/26	2.46	- Fixed the issue where some of the H.265 video resolutions transmitted from Wisenet 7 camera were unable to be decoded

Latest F/W Information

Network Camera

Technical Newsletter June 2023

Model	Filename	Date	Version	Release Note
LND/O/V-6012R/6022R/6072R LND-6032R	LNO-6072R_1.41.12 _20230426_R149	2023/05/09	1.41.12	<ul style="list-style-type: none"> - Fixed a problem that the NTP server time was not reset to match the changed NTP server when the NTP server address setting was changed - Added option to grant user permission to access and set settings on [Video profile], [Camera setup], and [Video and focus setup] ([Video setup] for models that do not support focus function) pages
PNM-12082RVD	PNM-12082RVD_2.21.00 _20220420_R134	2022/05/20	2.21.00	<ul style="list-style-type: none"> - Improved initial focus
PNM-7082RVD	PNM-7082RVD_2.21.00 _20220414_R104	2022/05/20	2.21.00	
PNM-8082VT	PNM-8082VT_2.01.01 _20210324_R175	2021/05/12	2.01.01	<ul style="list-style-type: none"> - Improved the issue of camera time failing to periodically sync with that of the NTP server
PNM-9002VQ	PNM-9002VQ_2.22.00 _20230418_R77	2023/05/01	2.22.00	<ul style="list-style-type: none"> - When setting the H.264/H.265 codec, you can set 10 kbps as the minimum bitrate.
PNM-9084QZ(RQZ)/1 PNM-9085RQZ/1	PNM-9084QZ_2.22.00 _20230418_R371	2023/05/01	2.22.00	<ul style="list-style-type: none"> - Displays the company name as Hanwha Vision in the web viewer - Added a function to configure the MTU (Maximum Transmission Unit) size between 1,280 and 1,500 in [Setup] > [Basic] > [IP & Port] > [IP address] - Fixed an issue where video streaming was interrupted for the live and recording in the camera registered to NVR or Genetec - Fixed an issue where firmware issued after 2022 did not upgrade properly - Fixed a problem where the certificate was not used normally when uploading a certificate with a '+' sign - Fixed an error where commands operate with a modified packet - Fixed an error where ONVIF discovery communication was not available between a camera and Wisenet Device Manager in a certain circumstance
PNM-9322VQP	PNM-9322VQP_2.22.00 _20230418_R151	2023/05/01	2.22.00	<ul style="list-style-type: none"> - When setting the H.264/H.265 codec, you can set 10 kbps as the minimum bitrate.
PNM-9022V	PNM-9022V_2.01.02 _20230404_R149	2023/05/11	2.01.02	<ul style="list-style-type: none"> - Improved functionality to obtain TTA security certification - Fixed an issue where Pan and Tilt operate beyond the maximum Pan/Tilt movement range set in the [PT Limit] menu - Fixed an issue where [Loitering] event was continuously sent to the NVR even though the loitering event had ended
PND-A6081RV/RF PNO/V-A6081R	PNO-A6081R_2.11.03 _20220519_R216	2022/06/09	2.11.03	<ul style="list-style-type: none"> - Fixed timestamp errors
PND-A9081RV /RF PNO/V-A9081R	PNO-A9081R_2.11.10 _20220519_R614	2022/06/09	2.11.10	
QND/O/V-7080R	QND7080R_Series _4.01_210706	2021/08/06	4.01	<ul style="list-style-type: none"> - Updated the unique certificate (expiration date: 2051-04-08)
QNF-8010	QNF-8010_2.10.02 _20220401_R411	2022/04/20	2.10.02	<ul style="list-style-type: none"> - Added certificate management function
QND-6011/6021 QNO-6032R QND/O/V-6012R/6022R/ 6072R/6082R	QNO-6082R_1.41.14 _20230316_R358	2023/03/28	1.41.14	<ul style="list-style-type: none"> - Fixed language error in Japanese version - Fixed an error where [Tampering detection] function did not operate after a certain time - Added the ability to set the minimum bitrate of a profile to 10 kbps - Added the ability to use HTTP and HTTPS at the same time - Fixed an error where the SNMP port opens while SNMP does not operate - Fixed an error where commands operate with a modified packet - Fixed an error where ONVIF discovery communication was not available between a camera and Wisenet Device Manager in a certain circumstance - Removed unnecessary PHP scripts
QND/O/V-8010R/8020R/8080R QND-8011/8021 QNE-8011R/8021R	QNO-8080R_1.41.05 _20230316_R321	2023/03/28	1.41.05	<ul style="list-style-type: none"> - Fixed language error in Japanese version - Fixed an error where [Tampering detection] function did not operate after a certain time - Added the ability to set the minimum bitrate of a profile to 10 kbps - Added the ability to use HTTP and HTTPS at the same time - Fixed an error where the SNMP port opens while SNMP does not operate - Fixed an error where commands operate with a modified packet - Fixed an error where ONVIF discovery communication was not available between a camera and Wisenet Device Manager in a certain circumstance - Removed unnecessary PHP scripts

Latest F/W Information

Network Camera

Technical Newsletter June 2023

Model	Filename	Date	Version	Release Note
QND/O/V-6012R1/6022R1/6072R1/6082R1	QNO-6082R1_1.41.05_20230426_R32	2023/05/09	1.41.05	<ul style="list-style-type: none"> - Fixed a problem that the NTP server time was not reset to match the changed NTP server when the NTP server address setting was changed - Added option to grant user permission to access and set settings on [Video profile], [Camera setup], and [Video and focus setup] ([Video setup] for models that do not support focus function) Pages - Fixed an error where [Tampering detection] function did not operate after a certain time - Added the ability to set the minimum bitrate of a profile to 10 kbps
QND/O/V-7012R/7022R/7032R/7082R	QNO-7082R_1.41.05_20230426_R125	2023/05/09	1.41.05	<ul style="list-style-type: none"> - Fixed an error where [Tampering detection] function did not operate after a certain time - Added the ability to set the minimum bitrate of a profile to 10 kbps
QNP-6250(H) QNP-6320(H/R)	QNP-6320H_2.21.02_20220809_R199	2022/09/05	2.21.02	<ul style="list-style-type: none"> - Added auto tracking function
XNO-6080R	XNB-6000_2.10.04_20230328_R683	2023/05/11	2.10.04	<ul style="list-style-type: none"> - When setting the H.264/H.265 codec, you can set 10 kbps as the minimum bitrate.
XND/V-6020R	XND-6020R_2.10.02_20220401_R596	2022/04/20	2.10.02	<ul style="list-style-type: none"> - Added certificate management function - Added [Exclusive PTZ control] function to give priority to PTZ control to a specific user and restrict control commands of other users - Added new options such as [Query string] and [TCP message], etc. for [Handover] settings - Added the option to use the Internet Control Message Protocol (ICMP) timestamp request message - Fixed to move the location of the overlay image using the cursor - Adjusted the RTP Payload buffer to improve compatibility with specific NVRs - Improved Web UI for selecting TLS protocol version to use for encrypted communication
XNO-6085R	XNB-6005_2.10.02_20220329_R589	2022/04/20	2.10.02	
XND/O/V-L6080(V/R)	XNV-L6080R_2.10.02_20220401_R578	2022/04/20	2.10.02	
XNV-6080(R/RSA) XND-6080 (R/V/RV)	XND-6080_2.10.02_20220117_R567	2022/02/07	2.10.02	
XND-6081RV(RF) XNV-6081R	XND-6081RV_2.10.02_20220329_R469	2022/04/20	2.10.02	
XND-8020R/8030R/8040R XNV-8020R/8030R	XND-8020R_2.10.02_20220401_R599	2022/04/20	2.10.02	
XND-8080R(RV) XNV-8080R(RSA)	XND-8080R_2.10.02_20220401_R615	2022/04/20	2.10.02	
XNO/V-6120R	XNO-6120R_2.10.02_20220117_R551	2022/02/07	2.10.02	
XNP-6120H	XNP-6120H_2.10.02_20220324_R696	2022/03/24	2.10.02	
XNV-6011(W)	XNV-6011_2.10.02_20220117_R573	2022/01/17	2.10.02	
XND/O/V-6083R(RV)	XND-6083RV_2.22.01_20230418_R307	2023/05/01	2.22.01	<ul style="list-style-type: none"> - Updated the open-source library version - Fixed the problem that the SD card status becomes "SD Error" when encrypting the SD card - Fixed an issue where bicycles or motorcycles were detected as people - TLS 1.0/TLS 1.1 not supported for SRTP (port:322) - Updated the curl library to the latest - Supports items corresponding to number 60 among DHCP options
XND/O/V-8082/9082(R/RV/RF)	XNV-9082R_2.22.01_20230418_R456	2023/05/01	2.22.01	
XND/O/V-8083R(RV)/9083R(RV)	XND-9083RV_2.22.01_20230418_R313	2023/05/01	2.22.01	
XND-C6083RV/C7083RV XNO/C6083RV/C7083R	XND-C7083RV_2.22.01_20230418_R392	2023/05/01	2.22.01	
XND-C8083RV/C9083RV XNO/C8083RV/C9083R	XND-C9083RV_2.22.01_20230418_R407	2023/05/01	2.22.01	
XNF-9010RV/RS/RVM	XNF-9010RV_2.22.01_20230418_R433	2023/05/01	2.22.01	<ul style="list-style-type: none"> - When setting the H.264/H.265 codec, you can set 10 kbps as the minimum bitrate. - Improved functionality to obtain TTA security certification - Fixed an issue where Pan and Tilt operate beyond the maximum Pan/Tilt movement range set in the [PT Limit] menu - Fixed an issue where [Loitering] event was continuously sent to the NVR even though the loitering event had ended
XNF-8010R(RV/RW/RVM)	XNF-8010R_2.10.04_20230328_R640	2023/05/11	2.10.04	
XNP-6400(R)/8250(R)/9250(R)	XNP-9250R_2.22.00_20230418_R330	2023/04/26	2.22.00	

Latest F/W Information

Encoder / Decoder

Technical Newsletter June 2023

Model	Filename	Date	Version	Release Note
SPD-150	SPD-150-PKG_v1.06 _210504171045	2021/05/11	1.06	<ul style="list-style-type: none"> - Fixed an issue where the profile of Live4NVR is created by default every time the camera is registered, causing the user's profile settings to reset.
SPD-151	SPD-151-PKG_v1.04 _210114190022	2021/02/01	1.04	<ul style="list-style-type: none"> - Fixed an issue where some H.265 resolutions could not be decoded in Wisenet 7 cameras.
SPD-1660R	SPD-1660R-PKG_v2.12 _210114194116	2021/02/01	2.12	<ul style="list-style-type: none"> - Fixed an issue where video is not displayed once in a while when switched to layout after connecting to SSM.
SPD-152	SPD-152_5.10.32 _230508130731	2023/05/10	5.10.32	<ul style="list-style-type: none"> - Deleted the function of synchronizing a decoder SPD-152 with a camera audio - Enable the sequence to operate in the latest layout configuration when the decode restarts after it reboots in operation of layout sequence functions - Increased the maximum number of layouts from 10 to 20 for layout configuration and operation of layout sequence
SPE-110	SPE110_1.31 _200310_1700	2020/03/25	1.31	<ul style="list-style-type: none"> - Supports video output setup
SPE-1610	SPE1610_1.31 _200310_1706	2020/03/25	1.31	<ul style="list-style-type: none"> - Provides the notification message "Live video cannot be played" on maximum streaming
SPE-1620	2.11.02_20220426	2022/04/26	2.11.02	<ul style="list-style-type: none"> - Improved Genetec compatibility
SPE-1630	SPE-1630_2.21.01 _20230309_R149	2023/03/24	2.21.01	<ul style="list-style-type: none"> - Added a function to display the time in "Month-Day-Year Hour:Minute" format if H.264 or H.265 codec is applied - Fixed an error where ONVIF discovery communication was not available between a camera and Wisenet Device Manager in a certain circumstance
SPE-410	spe410_1.31 _200310_1655	2020/03/25	1.31	<ul style="list-style-type: none"> - Added a function to display the time in "Month-Day-Year Hour:Minute" format if H.264 or H.265 codec is applied - Fixed an error where ONVIF discovery communication was not available between a camera and Wisenet Device Manager in a certain circumstance
SPE-420	SPE-420_2.11.03 _20220426_R142	2022/05/18	2.11.03	<ul style="list-style-type: none"> - Fix the problem that when you change the external PTZ connection port to COAX for all channels, the external PTZ settings item disappears in the webviewer

Software

Model	Filename	Date	Version
Wisenet SSM	2.13.00	2023/02/03	- Bug fixes and functional improvements
Wisenet Viewer	1.04.00	2023/05/23	- Bug fixes and functional improvements
Smart Viewer	4.9.13	2022/05/18	- Bug fixes and functional improvements
WiseNet mobile	2.05.03(Android)	2022/11/17	- Bug fixes and functional improvements
	2.05.03(iOS)	2022/11/17	

HDD Compatibility List

Revision 11.14

Release date : 2023.04.18

<https://www.hanwha-security.com/en/support/data-center/hdd-compatibility/>

Major change

1. HRD-435FN 6TB support -> Does not support
2. HRX-1632 -> ARD-1610